

# Secvest 2WAY Wireless Fire Alarm Button

Art.-Nr. FU8310

Seite 1 von 2



The Secvest 2WAY wireless fire alarm button is a detector of the Secvest (or the Terxon with a wireless expansion module). By pressing the button, you can easily and quickly trigger a fire alarm. In the Secvest, the wireless fire button assigns a zone with the "fire" characteristic. This zone is monitored and the button will trigger an alarm even when the alarm panel is disarmed. In the system settings of the Secvest, you can define whether a call should be made to an emergency call center in addition to the acoustic and visual alarm. With corresponding batteries (3V lithium) the wireless fire button has a service life of approx. 24 months. The range is approx. 30 meters.

## Technologies

- Convenient surface mounting
- Tamper monitoring
- Thermoplastic material
- Tamper monitoring

## Technical data - Secvest 2WAY Wireless Fire Alarm Button

Battery - max. battery life	2 y
Battery - type	3V CR2477N lithium battery
Colour	other
DC voltage supply	3 V
Dimensions	(WxHxD) 85x85x52 mm
Environmental class	II
Height	85 mm
Housing material	Thermoplastic material
IP protection class	32
Length	52 mm
Max. operating temperature	50 °C

# Secvest 2WAY Wireless Fire Alarm Button

Art.-Nr. FU8310

Seite 2 von 2

## Technical data - Secvest 2WAY Wireless Fire Alarm Button

Max. transmission range (building)	30 m
Max. transmission range (free field)	100 m
Min. operating temperature	-10 °C
Modulation	FM
Net weight	0,16 kg
PSTI conformity required	No
Radio frequency	868,6625 MHz
Radio power	10 mW
Sabotage monitoring	Yes
Security level	2
VdS class	none
Voltage monitoring	Yes
Width	85 mm