

Secoris 10" Touch control panel

Art.-Nr. IPBE60000

Seite 1 von 2



SMART & INTUITIVE ALARM SYSTEM OPERATION

The touch control panel has two operating modes: standard operating mode and detector zone display, each protected by a PIN code. The desired mode is set during installation.

Simply convenient: operate the Secoris by touch

In the operating mode, you control, arm (activate) and disarm (deactivate) the Secoris intruder alarm system with the same intuitive ease as in the Secoris app.

Status at a glance

In the detector zone display, all sub-zones and the opening detectors located in them are displayed together with their status (open/closed). In this way, the user is reliably able to see open doors and windows before arming the system. It can be set as a permanent display.

Discreet wall terminal

The touch control panel has a touchscreen with a 10.2 inch (approx. 26 cm) screen and the standard dimensions of a tablet PC. This makes it a flexible fit for any hallway or entrance area.

Easy to install

The touch control panel is integrated into the Secoris control panel via IP network (LAN, Wi-Fi) and supplied with power via the network (PoE), from a flush-mounted socket or with a plug-in power supply unit (suitable ABUS accessories: Powerline PoE adapter, mini built-in power supply unit or plug-in power supply unit). In this way, the control panels/terminals can be flexibly distributed throughout the building.

Technologies

- Tablet control panel with 10.2 inch (approx. 26 cm) touch display for easy operation of the Secoris intruder alarm system without buttons

Secoris 10" Touch control panel

Art.-Nr. IPBE60000

Seite 2 von 2

- Two operating modes can be set: standard operating mode or detector zone display
- Operating mode for conveniently arming and disarming (activating, deactivating) the intruder alarm system
- Can switch partitions, e.g. individual departments separately
- See status at a glance: the detector zone display shows the status open/closed for all access points (secured doors and windows) in all sub-zones
- Can be used flexibly anywhere in the building, with stable connection to the Secoris control panel, optionally via network cable (LAN) or Wi-Fi
- Quick, easy installation: Power supply via network cable/PoE (LAN operation) or power supply unit (Wi-Fi operation)
- Wall terminal for easy installation in the hallway or entrance area (wall mount included)

Technical data - Secoris 10" Touch control panel

Colour	White
Compatible with	Secoris
Connections	RJ45 Ethernet, supply voltage
DC voltage supply	12 V
Dimensions	254 x 166 x 26,6 mm
Display	10.1 inch Capacitive Touch-Screen
Environmental class	II
Fuse protection type	Intrusion protection
Gross weight	1,06 kg
Height	166 mm
Housing material	ABS
Installation location	Wall
Max. humidity	90 %
Max. operating temperature	50 °C
Min. operating temperature	-10 °C
Net weight	0,875 kg
Power consumption	96 mA
Sabotage monitoring	No
Width	254 mm