

Flush Mount Key-switch

Art.-Nr. SE1100

Seite 1 von 2



Use the flush mount key-switch to arm and disarm your alarm system. Simply turn the key instead of entering a PIN code. Operating your system is faster and easier. Apart from the arm/disarm function of the alarm system (or individual partitions), you can use the flush mount key-switch to control electronic equipment (entrance lighting, garage door, etc.). Two switch contacts are provided. You can set these as a permanent contact or as a pulse generator. The two colored LEDs inform you permanently about the state of connected devices. For example, you can see if the system is currently armed or disarmed. The reinforced fascia plate, the high-quality ABUS cylinder and a robust weatherproof housing (IP 55) protect the key-switch against external influences. The flush mount key-switch is designed for half-cylinders (10/30). It is available for both surface and flush fitting. The surface-fitted variant is protected from tampering by a cover contact and an anti-removal wall contact.

Technologies

- Arm and disarm by turning the key
- For flush mounting
- High security with pull protection and ceiling tamper switch
- Sturdy housing

Technical data - Flush Mount Key-switch

Compatible with	Secoris, Secvest, Terxon
DC voltage supply	10-15 V
Dimensions	(WxHxD) 106x134x42 mm
Height	134 mm
Housing material	ABS
IP protection class	55
Installation location	Flush fitting
Length	42 mm

Flush Mount Key-switch



Security Tech Germany

Art.-Nr. SE1100

Seite 2 von 2

Technical data - Flush Mount Key-switch

Net weight	0,45 kg
Power consumption	2 mA
Sabotage monitoring	Yes
Status display	Yes (2 LEDs)
Width	106 mm