

Secvest Wireless Fire Alarm Button

Art.-Nr. FUAT50020

Seite 1 von 2



Get help quickly and easily when a fire breaks out

At the simple touch of a button, the Secvest wireless fire alarm button can be used to rapidly trigger a fire alarm. The fire alarm can also be triggered when the alarm panel is not armed. All that's required is the simple touch of a the button.

Differentiation of alarm and emergency calls

You can decide for yourself whether just a visible and audible alarm is triggered or if an emergency monitoring station is also to be notified. Fitted with the correct batteries (3 V lithium batteries) the wireless fire alarm button will last for approx. 24 months.

Technologies

- Rapid and straightforward triggering of a fire alarm
- Tamper monitoring

Technical data - Secvest Wireless Fire Alarm Button

Battery - max. battery life	2 y
Battery - type	3V CR2477N lithium battery
Compatible with	Secvest, Terxon, BUM060040
DC voltage supply	3 V
Dimensions	(WxHxD) 85x85x52 mm
Environmental class	II
Height	85 mm
Housing material	Thermoplastic material
IP protection class	32
Length	52 mm

Secvest Wireless Fire Alarm Button

Art.-Nr. FUAT50020

Seite 2 von 2

Technical data - Secvest Wireless Fire Alarm Button

Max. operating temperature	50 °C
Max. transmission range (building)	30 m
Max. transmission range (free field)	100 m
Min. operating temperature	-10 °C
Modulation	FM
Net weight	0,17 kg
Radio frequency	868,6625 MHz
Radio power	10 mW
Sabotage monitoring	Yes
Security level	2
Voltage monitoring	Yes
Width	85 mm